

HALOGEN MARINE FLOODLIGHTS

Hobbs marine lamps are completely weatherproof. They are totally sealed against moisture ingress, and the mounting hardware is stainless steel to prevent rust and corrosion. The housing is shock resistant and can withstand up to 6 G's vibration. Both flood and spot versions are available to meet your lighting requirements. The flood pattern illuminates an area 80° wide by 30° long and the spot pattern projects a narrow beam of light up to 1000'.

Possible 4 x 6 applications include:

- Shrimp & fishing boats
- Off-shore oil rigs
- Ocean vessels
- Barges
- Dry dock lighting
- Freighters, tankers, etc.
- Pleasure craft
- Anywhere a corrosion resistant lamp is needed

Possible 3 x 5 applications include:

- Engine compartment lighting
- Deck lighting
- Emergency lighting
- Launching and docking
- Spreader lights



3 x 5 version with Spreader Bracket

Rectangular Marine Lamps (4 x 6)

| <i>Rated voltage</i> | <i>Wattage</i> | <i>Mounting</i> | <i>Beam Pattern</i> | <i>Current</i> |
|----------------------|----------------|-----------------|---------------------|----------------|
| 12V | 50W | Flush | Flood 80°x30° | 4A |
| 12V | 50W | Flush | Spot | 4A |
| 12V | 50W | Stud | Flood 80°x30° | 4A |
| 12V | 50W | Stud | Spot | 4A |
| 24V | 60W | Flush | Flood 80°x30° | 3A |
| 24V | 60W | Flush | Spot | 3A |
| 24V | 60W | Stud | Flood 80°x30° | 3A |
| 24V | 60W | Stud | Spot | 3A |

Sealed Beam Replacements (4 x 6)

| <i>Rated voltage</i> | <i>Wattage</i> | <i>Beam Pattern</i> | <i>Current</i> |
|----------------------|----------------|---------------------|----------------|
| 12V | 50W | Flood 80°x30° | 4A |
| 12V | 50W | Spot | 4A |
| 24V | 60W | Flood 80°x30° | 3A |
| 24V | 60W | Spot | 3A |

Rectangular Marine Lamps (3 x 5 - includes spreader bracket)

| <i>Rated voltage</i> | <i>Wattage</i> | <i>Mounting</i> | <i>Beam Pattern</i> | <i>Current</i> |
|----------------------|----------------|-----------------|---------------------|----------------|
| 12V | 50W | Stud | Flood 80°x30° | 4A |

Sealed Beam Replacements (3 x 5)

| <i>Rated voltage</i> | <i>Wattage</i> | <i>Beam Pattern</i> | <i>Current</i> |
|----------------------|----------------|---------------------|----------------|
| 12V | 50W | Flood 80°x30° | 4A |